

## P-5W - DMX Protocol



Protocol Rev. 1

Mode
1 Channels Mode

Valid From Firmware Version
2.30

Channel	Name	DMX Value		DMX Percentage		Description	Info	Default DMX Value	Fader Type
1	WHITE	0	255	0,0%	100,0%	No WHITE -> Maximum WHITE		0 (0%)	Fade

WHITE Control

## P-5W - DMX Protocol



Protocol Rev. 1

Mode
2 Channels Mode

Valid From Firmware Version
2.30

Channel	Name	DMX Value		DMX Percentage		Description	Info	Default DMX Value	Fader Type
1	Shutter	0	7	0,0%	2,7%	Closed		10 (3,9%)	Snap
		8	15	3,1%	5,9%	Open			
		16	151	6,3%	59,2%	Strobe	Fast -> Slow		
		152	175	59,6%	68,6%	Pulse - Open	Slow -> Fast		
		176	199	69,0%	78,0%	Pulse - Close	Slow -> Fast		
		200	244	78,4%	95,7%	Strobe - Random	Slow -> Fast		
245	255	96,1%	100,0%	Open					
2	WHITE	0	255	0,0%	100,0%	No WHITE -> Maximum WHITE		0 (0%)	Fade

WHITE Control + Shutter

## P-5W - DMX Protocol



Protocol Rev. 1

Mode
2 Channels Mode

Valid From Firmware Version
2.30

Channel	Name	DMX Value		DMX Percentage		Description	Info	Default DMX Value	Fader Type
1	WHITE	0	65535	0,0%	100,0%	No WHITE -> Maximum WHITE		0 (0%)	Fade
2									

16 BIT - WHITE Control